DOMETIC PGE121 PORTABLE INVERTER GENERATOR, 2100 VA



STAY AS LONG AS YOU LIKE

Never be caught without a reliable source of power with the Dometic PGE121 portable inverter generator. The Dometic PGE121 boasts powerful pure sine wave inverter technology with a maximum power output of 2100 VA. Fuel efficiency is maximised and noise is minimised thanks to the clever eco-mode technology which adjusts the engine RPM based on the connected load. You can run even the most sensitive appliances in the way that's most convenient for you, with three output types available: 12 V DC, 240 V AC, and USB. Moving the PGE121 around the campsite is easy, with built-in wheels and an extended handle ensuring that no heavy lifting is required.

- Powerful pure sine wave inverter technology
- High peak power output of 2100 VA and continuous output of 1800 VA
- Retractable handle and robust wheels for easy transportation
- Can be easily stored upright or on its side when the fuel is turned off
- Outputs include 2 x 240 V AC sockets, 1 x 12 V DC socket and 2 x USB sockets



MULTIPLE OUTPUT OPTIONS Ability to power appliances with 12 V DC, 240 V AC or USB power



TELESCOPIC HANDLE Easily extend the handle to suit your height



ROBUST WHEELS Built-in wheels for simple manoeuvering

SPECIFICATIONS

Ref No. 9600027157 Dimensions W x H x D (mm) 530 x 430 x 320 Weight (kg) 26.5 Fuel Tank Capacity (I) 4.2 Engine Oil Capacity (I) 0.35 Fuel 4-stroke unleaded petrol Ignition System CDI	DOMETIC PGE121	
Weight (kg) 26.5 Fuel Tank Capacity (l) 4.2 Engine Oil Capacity (l) 0.35 Fuel 4-stroke unleaded petrol	Ref No.	9600027157
Fuel Tank Capacity (I) 4.2 Engine Oil Capacity (I) 0.35 Fuel 4-stroke unleaded petrol	Dimensions W x H x D (mm)	530 x 430 x 320
Engine Oil Capacity (I) 0.35 Fuel 4-stroke unleaded petrol	Weight (kg)	26.5
Fuel 4-stroke unleaded petrol	Fuel Tank Capacity (I)	4.2
	Engine Oil Capacity (I)	0.35
Ignition System CDI	Fuel	4-stroke unleaded petrol
	Ignition System	CDI



Mobile living made easy.